

EL-2 Addressable Control Panel

Features:

- ▶ Complies with BS5266 for open areas
- ▶ Supports 2 lighting lines with 127 points per line
- ▶ Slim profile - only 100 mm deep
- ▶ Robust design

Description

The EL-2 emergency light control panel features two lines, each line can accommodate 127 FIREscape devices. The EL-2 supplies the operational voltage to the light units during normal conditions, whilst also completing the continuous testing and monitoring of the equipment on the system.

All monitored event information is saved in the memory of the control panel, and this can be accessed by a connected EL-KP key pad

NOTE: Must be used in conjunction with the EL-35V Transformer



Specification

Number of lights/signs supported	254
Connection voltage	35 V ac (222 VA)
Nominal voltage	12 V dc
Internal battery capacity	7.2 Ah
I/O outputs	2 relay outputs
Modem/PC connection	RS-232
User panel connection	RS-485/9600 baud
Event memory	500 events
Dimensions (mm)	295W x 475H x 100D
Material/Colour	Sheet steel, powder-coated/White
Weight including batteries (kg)	8