



BK Radio DPH-CMD Portable Radio Specifications

DPH-CMD

INCLUDED

- Dual Priority Scan
- Tone Code Guard (CTCSS)
- Digital Tone Guard (CDCSS)
- Analog DTMF Encode
- Analog DTMF ANI
- Timeout Timer
- Nuisance Channel Delete
- Talkback Scan
- Soft Switch Programming
- User pick lists for tone and digital guards
- Network Access Codes
- Talk Group IDs
- Streamlined Unit-To-Unit Calling
- Programmable Unit-To-Unit Callback
- Emergency Transmission Mode

Signal Selection:

- RX – Automatic Digital/Analog
- TX – Automatic Digital/Analog
- TX – Selectable Digital/Analog

GENERAL SPECIFICATIONS

Channels	500
Operating Voltage	10V. NOM.
Operating Frequency Range	136-174 MHz
Operating Temperature	-30° to 60°
Current Drain:	
Standby	20 mA
Receive	255 mA
Transmit	1.5A
Stability	+/-2.5 PPM
Channel Increments	2.5/6.25/7.5 KHz
Channel Spacing	25/30 and 12.5/15 KHz
Size - W x D x H	
(Standard Battery)	2.55 x 1.5 x 6.6 in.
Weight w/Std Battery	20 oz.
Antenna	Helical Wound, Molded Rubber Flex

TRANSMITTER

RF Output (Hi-Lo)	5/2	5/2
Spurious and Harmonics	60 dB	60 dB
Hum and Noise	50 dB	45 dB
Audio Distortion	3%	3%
Audio Response (per EIA)	+1/-3 dB	+1/-3 dB
Modulation	16K0F3E	11K0F3E
	8K10F1D	8K10F1E

RECEIVER

Sensitivity	-119 dBm	-119 dBm
Selectivity	72 dB	60 dB
Spurious including Image	75 dB	75 dB
Intermodulation	70 dB	70 dB
Audio Output @ 5% Distortion	500 mW	500 mW
Audio Response (per EIA)	+1/-3 dB	+1/-3 dB



155 Spring Hill Dr. - Ste. 201 - Grass Valley, CA 95945
 Toll Free: 800-552-0707 Office: 530-477-2590 Fax: 530-477-9188
www.49ercom.com



BK Radio DPH-CMD Portable



**New Command & Control Digital Radio
for large-scale operations**

Making reliable communications affordable





Specially engineered for managing multi-unit, wide-area response

- 500 channels, 25 user groups, 20 channels per group
- 136-174 MHz VHF expanded frequency range
- 5/2 Watts RF output
- Enhanced keypad simplifies label programming in the field, plus programmable soft switches and options
- Rock-solid reliability – meets tough MIL-STD 810 and approved by the California Dept. of Forestry
- Channel increments – 2.5/6.25/7.5 KHz; channel spacing – 25/30 and 12.5/15 KHz
- Global TX Code Guard Select – 32 TX-tone global pick list for field selection, network access codes, and talk group IDs
- Channel and priority (dual priority) scan, talkback scan
- Enhanced dot-matrix display – two-line, 12-character alphanumeric icons
- Nuisance channel delete
- Meets or exceeds APCO P25 specifications including FDMA Common Air Interface compatible, emergency group calls, and unit-to-unit calls with auto-callback
- Programmable for digital, analog, or true mixed-mode operation, with automatic mode detection and talkback
- Easy to use, easy to program and customize
- Superior audio quality and clarity
- Weatherproof design
- Longer life between battery charges/changes – over 19 hours with high-capacity lithium-ion battery
- On-demand Command Group – enables building a 20-channel command group from any of the 500 programmed channels on the fly
- Tactical Scan Group



- Enhanced user-selectable per-channel code guard for finding the best signal path without changing channels
- Cloning technology transfers information from one radio to another automatically – global data, group data, command group, pick lists
- FLASH technology enables future enhancements via software instead of hardware changes

The BK Radio DPH-CMD portable, compliant with the APCO P25 standard, including the P25 FDMA Common Air Interface, has all the capabilities of the proven DPH, plus enhanced feature sets engineered to meet additional advanced requirements specified for first-responders for tactical command-level radios.

The DPH-CMD portable combines proven rock-solid reliability with extreme versatility and ease of use. Each radio can be customized to provide the range of functions you need to meet your specific situation and requirements. The new Command Group feature allows you to create a custom command group on the fly. User pick list of 32 code guards for field selection.

Its superior design means that functions and features are software-driven, creating inherent efficiencies that result in significant cost savings without compromising or sacrificing quality, performance, reliability, or durability even under the most demanding public safety conditions.

Programming is focused on the practical needs and requirements of the radio user. Despite a wide

variety of individual options, the BK Radio DPH-CMD portables are always easy to use – a critically important factor in emergency situations.

As a result of advanced engineering techniques, the DPH-CMD and all D Series portable radios have lower current drain than other portables, which means significantly longer battery life between battery charges or changes. And with the new high-capacity lithium-ion battery, service cycles are extended to more than 19 hours.

The DPH-CMD also has the ability to clone group information to other DPH-CMD models.

Additional economies are realized by using the accessories you already have for other BK Radio units such as antennas, microphones, batteries, cloning and programming cables, and carrying cases.

All 500 channels can be programmed for digital operation, analog operation, or both. Frequencies programmed for mixed-mode operation recognize the format of the received signal and automatically transmit in the same format.

